

PS-55AT Special Application Power Supply



- Designed for automation and PLC-based applications
- Error-proofing capabilities for process verification
- High and low speed settings
- LED visual indicators for start, stop and cycle complete

Key Features and Information

- For single tool use:
 - TL Series
 - Alpha Series
 - CL-Series (up to 6500 model)
 - SS-Series (up to 6500 model)
- Inputs for tool enable and disable
- Outputs for cycle complete
- Switchable two-speed output delivers a full 30 VDC on "high" and 20 VDC on "low" settings

Power Supply Back Panel Detail

- Removable AC Power cord is easily replaced if damaged.



ASG Part Number	Model Number	Max	Circuit Controller	Safety	Approx. Output	Input	Size	Weight
65707	PS-55AT	2.5 amp	Built-in	3A Fuse (Input) 4a Breaker (Output)	20-30 VDC	110-120 or 220/240 VAC	3.5"(W) X 7.1" (D) X 4" (H)	6.5 lbs

Quality Certified ISO 9001:2008

ASG, Division of Jergens, Inc.
Jergens Way, 15700 S. Waterloo Road
Cleveland, OH 44110-3898

Toll Free: (888) 486-6163 | Fax: (216) 481-4519

Email: asginfo@asg-jergens.com | www.asg-jergens.com