



## BTL Brushless Electric Screwdrivers

### NEW Models! BTL-20 and BTL-30

- High quality brushless motor guarantees outstanding output torque and durability with low maintenance
- Easily switch between lever start and push-to-start
- Internal speed adjustable from 100 to 950 RPM
- Excellent torque repeatability
- Ergonomic design, small, and light weight
- Full torque output under lower RPM <sup>1</sup>
- Quiet
- Use only recommended power supply
- Compatible with the ASG STC-02 (ASG #65646) screw counter



**Recommended Power Supply:**  
BTL-5A (ASG #65710)



**Optional Screw Counter:**  
STC-02 (ASG #65646)

Model Number	Operation	Drive Size	Torque Range		Speed RPM	Voltage	Length		Weight	
			lbf.in	N.m			mm	in.	g	lb.
BTL-20	Lever/Push-to-Start	1/4" Hex	2.7 - 17.7	0.3 - 2.0	100 - 950	DC 30V	290	11.4	720	1.6
BTL-30	Lever/Push-to-Start	1/4" Hex	4.4 - 26.5	0.5 - 3.0	100 - 950	DC 30V	290	11.4	720	1.6

<sup>1</sup>When operating under 300 RPM, the max torque output of the BTL-30 will be less than 2.0 N.m (17.36 lbf.in)